

UAD0021-01: HP Laptop xx90 Adapter

Technical Datasheet

WE. ARE. *CRITICAL. POWER.*™



Technical Specifications	
Part No.	UAD0021-01
Input Voltage	11 to 16VDC
Output Voltage	19VDC
Output Current	5.0A max. Fused at 15A
Connectors	BONDI
Size	5.0 x 3.0 x 1.15in
Length	.91m (36in)
Weight	12oz
Color	Black
Exterior/Housing	Aluminum

Features

- Output short circuit shut down
- Output current limit
- Input noise filter
- Internal overtemperature shut down
- Low input voltage shut down
- High input voltage shutdown
- Automatic shut down reset

Applications

- This adapter will operate the laptop and charge its battery from any xx90 battery:
 - UBI-390 / BB-390/U
 - BB-590/U
 - UBI-2590 (UBBL02) / BB-2590
 - UBBL09/B
 - UBI-2590 SMBus (UBBL10)
 - UBI-2590 HC SMBus (UBBL13)
 - UBI-2590 SF SMBus (UBBL36)
 - UB0023 (BA-5390A/U)
 - UB0031 (BA-5390 CFx)
 - UB0032 (BA-5390 SF CFx)